

# **BT-301 Battery Condition Analyzer**

----Internal resistance and conductance switchable

The BT-301 Battery Tester is very effective and economical battery management device for testing battery internal resistance (or conductance) and voltage. It helps you eliminate weak batteries to ensure performance of your battery systems.

It is capable for accurate measurement of Valve Regulated Lead Acid (VRLA), Vented Lead Acid (VLA) batteries and Ni-cd batteries which are the main composition of standby critical power systems. This battery tester is widely applied for service providers, operations and maintenance teams for battery management and measurement to ensure power integrity in telecom networks, data center, power utility, forklift maintenance and so on.

#### Unique Advantages

- Multilingual: English, Spanish, Germany, French and more to come
- Two units in one, smart switch to test internal resistance and conductance of battery.
- Including rugged test clamp and 2-section pin probe for different battery conditions
- Wide test range up to 6000Ah for Lead-Acid or Nickel-Cadmium single battery up to 16V
- · Field proven accurate and repeatable measurement to identify battery health.
- Very fast and consistent test of battery or multiple batteries simply in several seconds
- It adopts advanced measurement way of AC signal discharge to test internal resistance
- User friendly TFT touch screen and keypad as alternative operation
- · Universal micro-USB for firmware update, data export and battery charging
- Functional management software on PC for recording, analyzing measurement data and easy report printing out.
- Battery pack is durable in the field with testing time of 8-12 hours
- · Up to 100,000 cells stored internally, unlimited with USB drive exportation

# **Functional PC Software**

Kongter Data View software provides smart solutions for data analysis, battery condition tracking and report generation in Excel. This PC software is also expandable for battery management along with Kongter's other battery test equipment including load bank, battery data logger, battery charger and so on. It is functional and powerful for compete data trending and analysis of your batteries.

# **Application:**

- Telecom & communication power
- Uninterrupted Power Supplies (UPS)
- Utility transmission and distribution systems
- Data center, healthcare, education or financial
- Forklift and traction battery maintenance
- Refinery, mining and offshore platform
- Battery manufacture and inspection

Dars Management - Registerior Tenter	And I wanted to show that the	- Contract of the local division of the loca				
No Control dwip						
SS 10 12 11 11 11 12 12 12 12 12 12 12 12 12		Ċ,				
🖬 sint at face 🔤 Ental Satu by Residence Feder (String-1657 - 51.)						
Ring Cavillan Histophy	Text Details					
sets fast and have been fail and discount	- Note	Wheel	Sedawickin(2)	Caparity/NO	Condition	
No.		1111	6.178		1.000	
		2,001	1.151	1005.000	(Asso.)	
		2.962	1.133	100.000	(Face	
·		1.197	LIN	101.008	Face	
	Number 1	2484	1.133	101.008	Fees	
		2004	1.098	1010.008	Paca .	
Rec) for	- 7	2000	1.010	100.000	Pass	
		2487	1.199	100.000	Pass	
		2.045	5.003	1010.000	Face	
	10	2258	8.003	101.006	dare .	
	11	1192	1.000	1010.008	Fare	
1 H	Jo U	2.043	1.197	100.000	Fass	
	12	2048	L114	UNLODE	Fast	
	- 14	2014	3.281	10.000	Test .	
COM Part and the Add and Add and	15	2046	1.629	228.000	Pass	
	10	2.087	1.347	16.000	Reco	
	17	2487	1.003	1010,000	Pass :	
	18	1092	1.003	1010.000	Pass	
		2.045	1.344	088,000	Pass	
* it	20	2.047	1.123	105.008	Pass	
	and a second	1341	1.096	105.000	(Paid )	

Functional PC software



Wide applications



Packed in rugged carrying case



# **Technical Specification**

Technical Specificatio	[]			
Applications:	Test single Lead-Acid or Nickel-Cadmium cell or battery string (one by one after setting once). Cell types supported: 1.2V, 2V, 6V, 12V and other			
	customized types up to 6000Ah.			
	Internal Resistance:			
Resistance range	0.001 mΩ100mΩ			
	100 - 19,990 Siemens			
Voltage range	0.000V ~25V			
Test Data Storage:	100,000 cells stored internally, unlimited with USB			
	drive exportation			
Minimum test resolution				
- resistance	0.001mΩ			
-Voltage	1mV			
- Voltage				
Test accuracy				
-conductance	Resistance/Conductance: 2%			
-voltage	Voltage: 0.5%			
-vollage				
	Customized battery types			
User Programmable	Low voltage alarm setting			
Functions:	High resistance alarm setting			
	Test mode (push button/touch screen/auto start)			
	• 2-section Pin probe			
Cable Options:	Alligator Test Clamp			
	Custom cables by quotation			
	Li-ion battery (4000mAh), 8~12hours working time			
Power supply	after full charge			
Data Transfer:	3			
Data Transfer:	USB via micro-USB cable			
Storage Temperature:	-20~50℃			
Operation environment	0℃ to 40℃, 90% R.H			
Over Voltage Protection:	Auto-reset disconnect			
	Reverse polarity protected			
Measuring cells per string	1≤cells≤254			
LCD display	272*480 pixel, 4.3" TFT Touch Screen LCD			
Housing Material:	Acid resistant ABS plastic santoprene overmold			
Tester Dimensions:	L186*W98*H40 mm			
Weight:	Main body: 0.45KG			
	Package: 3Kg			
Standard:	CE Marking, EMC standard			

#### Standard composition:

- Main body
- 2-in-1 test clamp
- 2-section pin probe
- Carrying case
- Battery charger
- USB
- User manual



# Hardware Features

Quick plug-in connector for testing clamp or pin probe on top of the main unit:



Universal micro-USB for firmware update, data exportation and internal battery charging.



#### Test clamp:

BT-301 includes one set of test clamp (2-in-1) for quick test of battery internal resistance and voltage.

This rugged clamp set has metal jaw of 6cm long and 3mm thick, small but strong enough to connect battery posts in most ways of battery connections. Inner jagged structure is also useful for removing oxide on battery post. This ensures makes measurement result

# **Pin Probe:**

For quick test of batteries with contact surface as small as 3mm and 1.3mm (2 points) of battery posts.

The pin probe is composed of 2 sections which make it extendable to longer length for easy measurement of different battery wiring structures. Section 1 length is 23cm. With extension, length is 39cm.

# Order Info:

BT-301P (Base Kit with pin probe)BT-301T (Base Kit with testing clamp)BT-301C (Complete Kit with both pin probe and testing clamp)



Kongter Test & Measurement Co., Limited #405, Bldg 62, Songpingshan, Langshan Rd., Shenzhen China TEL: +86-755-2691 6832 Web: www.kongter.com Email: sales@kongter.com

